



# Entrée Wireless™

## Warrior Battery Pack AC Power Kit Specification Model WBK-4AM

The WBK-4AM is a prepackaged AC Inverter/battery-charger kit designed to support the AC and DC power needs in remote or temporary applications that require PDA, Laptops, etc.. The kit is small, light weight and protected so it can be thrown behind a seat or in the trunk for emergency use.

The WBK is truly an all-in-one solution as there is room in the case to store documents and additional equipment as required.

When combined with a SLA or standard (vehicle) lead acid battery, it provides 400W of AC power and a 10A - 12V DC output (Vehicle power outlet). The kit includes bolt-on and clip-on jumper cables for connection to a battery.

The 12V vehicle power outlet can be used to connect with laptop or PDA card adaptors

The WBL supports recharging the battery from AC power. The fast multimode charger will charge at full power until the battery is fully charged and then falls back to a trickle charge mode. The battery may be charged continuously without damage.

If recharging from another battery or vehicle is required, standard jumper cables are recommended.

**CAUTION** – Disconnect power adaptors when connecting the battery. They may not be reverse polarity protected

### AC Output / Inverter

- 400W AC modified sine wave
- Dual AC outlets
- Automatic battery cutoff
- On-Off switch

### DC output

- 12V Vehicle Adaptor
- Fuse 3AG 20A

### Battery Charger

- 3A fast/trickle multi mode charger
- Charger Status LED – ready, charge, fault
- SLA or standard 12V lead acid batteries
- Battery size – 7Ah – 200Ah

### Battery Connections Cables

- Bolt on battery cables
- Clip on Battery cables

### Physical

- Light duty water resistant case
- Size - 15.5"L x 11.5"W x 3.5"D
- Mounting plate – 12.5" x 9.5" x 2.5"D
- Weight – 6 lbs, Color - Black

## Typical Application - Portable AC Power Kit

